# MegaVox PRO PA System


## **Technical Specifications**



Thousands report the MegaVox PRO as the most reliable Public Address system on the market. Emergency responders like its signal alert siren, wired microphone and convenient shoulder strap. Coaches, band directors and auctioneers appreciate the flexibility of the AC/DC operation and the range of the wireless microphones.

With the MegaVox Pro you're ready for any situation . . . it's lightweight, loud & easy to carry. Just grab it and go!





(MEGA-7500U2 Back Panel Shown)

#### **MEGAVOX MODELS**

MEGA-7500 Battery powered PA system

wired microphone & built-in rechargeable battery

MEGA-7500U1 One built-in wireless receiver

MEGA-7500U2 Two built-in wireless receivers MEGA-7501 Unpowered companion speaker

#### **Features**

True AC/DC, 110/220V power supply

20 Watts Peak Power

Reaches a distance of 100 yards

Lightweight - Only 15 lbs

High-efficiency re-entrant horn driver

Powerful horn amplifier

Up to two built-in 16-channel UHF wireless receivers

Built-in rechargeable battery runs up to 10 hours on a charge

Microphone with coil cord


Signal alert button

External speaker output

External output powers optional MegaVox Pro companion speaker

Durable injection-molded case is tough, fade resistant & UV treated

Speaker stand receptacle molded into case bottom



### **UHF WIRELESS**

WH-6000 Wireless handheld microphone/ transmitter

Wireless body-pack transmitter WB-6000 (requires handsfree microphone)

> Microphone options include: Over-the-Ear/EM-TA4F, Lapel/LM-60, Collar/CM-60, Headband/HBM-TA4F

#### **TECHNICAL SPECIFICATIONS**

Rated Peak Power 20 watts Max SPL @ Rated Power 119 dB @ 1 meter Frequency Response 400 Hz - 10 kHz 18V DC/universal input Charger (RC-6000) (100Vac - 240Vac, 50 - 63Hz) 12 volt rechargeable, 5 AH **Battery** 

Dimensions (HWD) 13"x 9" x 14" (33 x 23 x 36 cm) Weight

15lbs / 6.8 Kg

Inputs Line

Hi-Z, unbalanced, 1/4"-phone Lo-Z, unbalanced, 1/4"-phone Mic 1 (used for wireless on MEGA-6000U1)

Mic 2 Outputs

Line (post fader)

Speaker Out  $4\Omega$ , unswitched, 1/4''-phone

Lo-Z, 1/4"-phone

Lo-Z, unbalanced, 1/4"-phone

CE ROHS

(Features & Specifications Subject to Change Without Notice)

**Anchor Audio, Inc.** 800.262.4671

Portable Sound Systems • Carlsbad, California www.anchoraudio.com